

DIWAC

DIGITAL WALLMOUNT
AUDIO CONTROLLER



CONTROLLER FOR AUDIOCONTROL12.8

The DIWAC wall mount controller is ideal to control the AUDIOCONTROL12.8 in every single room. The wall mount controller is programmable via the host's unit's graphical installer interface to allocate the functionalities you need. Via the GII you can program the wall control to trigger macro's or even control 3rd party devices.

The Graphical Installer Interface) has been developed to be extremely installer-friendly, this makes it possible for every integrator to configure the required unique solution. The variety of installations where AUDIOCONTROL12.8 can be used is endless and only limited by the installer's creativity.

DIWAC fits into most standard in-wall boxes such as our E-MODIN and N-MODIN.

- Inconspicuous and elegant design
- Easy and foolproof 2-wire system
- Polarity-independent wiring system
- Phantom powered over the communication wire
- Industry standard in wall chassis dimensions
- Invisible mounting (no mounting tools required) of the main control unit on the wall chassis
- Hardwired addressing
- 2 x 12 characters white backlit LCD display
- Automatic power save function
- Preconfigured for immediate plug & play use on supported systems
- Functionality is reprogrammable via the master unit's graphical user interface
- For indoor use only

TECHNICAL SPECIFICATIONS

Dimensions	83 x 83 x 9 mm
Cut-out dimensions	approx. 51 mm diameter or 51 x 51 mm minimally
Mounting depth	minimally 20 mm
Connectors	2-pole connectors up to 2.5 mm
Fits in	E-MODIN and N-MODIN
Weight	72 g including wall mount chassis
Power supply	24 VDC/110 mA max, phantom powered by main unit
Accessories	wall mount quick-fit chassis, 2-pole connector