

# LD-1024BOX-E

B05031

## DESCRIPTION

1024 Channel DMX interface for live-shows and light automation

## FEATURES

- 1024 Channel DMX interface for live-shows and light automation.
- Can be connected to your computer via USB (cable included) or via Ethernet (LAN / WLAN).
- 1024 Channels in Stand Alone (300KB internal memory = 100 to 1024 DMX steps).
- Up to 2 Artnet universes per connected box to the PC when using the LED PLAYER or PRO DMX software. The Artnet will be sent over the RJ45 network connector of your PC.
- Up to 8 Artnet universes per connected box to the PC when using the PIXXEM software !
- Infrared receiver (with optional IR remote).
- 1 NEXT button for scene selection.
- 30 Minutes Timeline for synchronized Lighting, audio and video loops ! (Pro DMX software).
- Works with the Chromateq Led Player, Pro DMX and the Pixxem software (included).
- 3-pin XLR connectors.
- Power supply for the use in standalone mode: 5V DC, 0.2A (adapter not included).
- An optional external infra-red receiver can be connected to the unit (LD-512Kit-IR = IR receiver + 2 remote controllers).
- For more information about the software: [www.chromateq.com](http://www.chromateq.com)



[www.briteq-lighting.com](http://www.briteq-lighting.com) | <https://www.facebook.com/Briteq>

Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2022 by BEGLEC NV. All rights reserved.



## TECHNICAL SPECIFICATIONS

<b>General : Dimensions (cm)</b>	7 x 9 x 5
<b>General : Weight (kg)</b>	0.23
<b>General : Powerinput</b>	USB 5Vdc
<b>General : Energy Label</b>	No
<b>General : Color</b>	No
<b>General : Display</b>	No
<b>General : IP rating</b>	indoor
<b>Control : Protocol</b>	Art-Net, sACN, DMX
<b>Control : programmable</b>	Yes
<b>Control : upgradable software</b>	Yes
<b>Control : maximum DMX channels</b>	1024
<b>Connections : input</b>	usb, RJ45
<b>Connections : output</b>	3 pin XLR
<b>Brand</b>	BRITEQ
<b>EANCode</b>	5420025650311

## YOUR DEALER



[www.briteq-lighting.com](http://www.briteq-lighting.com) | <https://www.facebook.com/Briteq>

Beglec NV has the right to change products and specifications with and without notice. Major as well as minor changes can be involved. This leaflet can contain errors, therefore we advice to consult your local dealer to ensure that actual features and specifications match your requirements. Copyright © 2022 by BEGLEC NV. All rights reserved.