

The Showtec DMX Merge allows you to combine two DMX controllers to one DMX line or to use a second desk as back-up desk.

The unit has 3 modes:

1) HTP (High Take Precedence) In this case you can use two similar desks with the same addressing on one line. The DMX channel with the highest value has priority.

2) Back-up mode. The unit is connected to two DMX desks. Channel A has priority. Once channel A fails or has no DMX channel B takes over the show.

3) Merge mode. Two desks can be merged on one line. E.g. you can run a scene setter and DMX operator on one line. The Scene Setter will operate on channel 1-96 and the DMX Operator will have the channels 97 and higher.

These positions can be freely addressed by the dip-switches.

Specifications

Voltage: 230V

Power Requirement: DC 9V, 300 mA Min.
(AC/DC adapter included)

DMX Input: two 3-pin

XLR male sockets on the front panel

Extra: two 3-pin

XLR male sockets on the rear panel

DMX output: two 3-pin

XLR female sockets on the front panel

Extra one 3-pin XLR

female sockets on the rear panel

Dimensions: 483 x 73 x 45 mm (LxWxH)

Weight: 1,15 kg